

Automatic Voltage Regulators (AVR) Selection Chart

AVR	Field Output Ratings (DC)			Sensing Circuit Ratings (AC)				Power Input Ratings		Regulation Accuracy	Parallel Compensation CT	Over Excitation O/V	Frequency Compensation U/F	Remarks
	Model	Field Rated Volts	Field Rated Amps	Field Forcing Volts	1PH	3PH	Voltage VAC	Frequency Hz	Voltage VAC					
EA05A	63	5	90	O		220/380/480	50/60	100~300	50/60	< ±0.5%			O	Universal 5 Amp AVR
EA05AF	170	5	170	O		220	50/60	160~260	50/60	< ±1%			O	Universal 5 Amp Full Wave AVR
EA15A	63	15	90	O		220/380/480	50/60	100~300	50/60	< ±1%	N:5		O	Universal 15 Amp AVR (Parallel applicable)
EA15A3H	90	15	90		O	220/380/480	50/60	120~300	50/60	< ±1%			O	Universal 15 Amp 3 Phase Sensing AVR
EA04A	32/64	4	42/85	O		110/220	50/60	110/220	50/60	< ±1%			O	Basler* VR63-4A compatible
EA42-7	42	7	90		O	220/380/480	50/60	220~260	50/60	< ±1%	N:1		O	Basler* VR42-7 compatible
EA63-4	63/100	4	63/100	O		110/220	50/60	90~139	50/60	< ±1%			O	Basler* VR63-4 compatible
EA63-2.5	63	2.5	100	O		220	50/60	220	50/60	< ±1%			O	Basler* VR63-2.5 compatible
EA460	43/90	4	43/90	O		110/220	50/60	110/220	50/60	< ±1.5%			O	Newage* SX460 compatible
EA440	90	4	90	O		220	50/60	170~265	50/60	< ±1%	N:0.33		O	Newage* SX440 compatible
EA341	120	2.7	120	O		220	50/60	170~220	50/60	< ±1%	N:0.33		O	Newage* MX321 compatible
EA321	120	3.7	120		O	220	50/60	170~220	50/60	< ±1%	N:0.33		O	Newage* MX341 compatible
EA-KOH	-	0.2	-	O		220	50/60	10-26DC	50/60	< ±1%			O	Kohler* Photo-Couple AVR compatible
EA15AH	90	15	90	O		220	50/60	170~265	50/60	< ±1%				For Carbon Brush Generators
EA15AF	180	15	180	O		220	50/60	170~265	50/60	< ±1%				For Carbon Brush Generators
EA45AH	90	45	90	O		220	50/60	170~265	50/60	< ±1%				For Carbon Brush Generators
EA45AF	180	45	180	O		220	50/60	170~265	50/60	< ±1%				For Carbon Brush Generators
EA75AH	90	75	90	O		220	50/60	170~265	50/60	< ±1%				For Carbon Brush Generators
EA75AF	180	75	180	O		220	50/60	170~265	50/60	< ±1%				For Carbon Brush Generators
EA150AH	90	150	90	O		220	50/60	170~265	50/60	< ±1%				For Carbon Brush Generators
EA150AF	180	150	180	O		220	50/60	170~265	50/60	< ±1%				For Carbon Brush Generators
EA03A	85	3	85	O		(110V) 18	50/60	60~90	50/60	< ±1.5%				For Small Generators
EW05	45	5	45	O		110		90~130						For Welder Generators

*For reference purpose only, not genuine Denyo / Basler / Newage / Kohler products

Please link to <http://www.kutai.com.tw> for brochure & detailed manual.